

# Product Environmental Profile



## COUNTIS P0x

Single phase modular active-energy meters



### The commitments of Socomec to respect the environment

As part of its environmental policy, Socomec is committed to:

- Incorporate the principles of the circular economy into the design of new products and services
- Promote longer product lifetimes
- Promote the use of environmentally responsible materials
- Design and develop solutions to further improve the energy efficiency of our products and services
- Inform our customers in a transparent manner about the environmental impact of our products throughout their life cycle.

To this end, Socomec is committed to constantly monitoring, anticipating and complying with environmental regulations as well as customer expectations relating to its products, and to ensuring that all those involved adhere to and take responsibility for its commitments.

Socomec is member of :

**ecosystem**



Member of WEEE Europe

**Gimélec**



Environment and sustainable development commissions

PEP ecopassport® Registration number: SOCO-00113-V01.01-EN

SOCOMECS.A.S

Head office : 1, rue de Westhouse – F – B.P.60010 – 67235 Benfeld Cedex

Tél : 03 88 57 41 41 – Fax : 03 88 57 78 78 – [www.socomec.com](http://www.socomec.com)

Contact : [http://www.socomec.com/contact-us\\_en.html](http://www.socomec.com/contact-us_en.html)

**socomec**  
Innovative Power Solutions

## ● Product information :

### Reference product

The representative product is the COUNTIS P04 with sales reference 48505004 with the following description: COUNTIS P0x are single-phase modular electrical energy meters that enable viewing of the different energies consumed and produced.

### Other covered references

This PEP covers other references listed in the table at the end of the document.

### Functional unit

Perform metering and displaying of electrical energy during a reference service life of 10 years.

## ● Materials and substances

### Declaration of the constitutives materials

Total mass of the reference product (including packaging): 0,13 kg among which packaging: 0,04 kg

For the reference product:

Plastics as % of weight		Metals as % of weight		Other as % of weight	
PC	25,04%	Steel	9,63%	Electronic components	28,09%
PE	6,26%	Copper and its alloys	4,49%	Cardboard	15,57%
				Paper	10,75%
Other plastics	0,16%				
<b>Total Plastics: 0,04 kg</b>		<b>Total Metals: 0,02 kg</b>		<b>Total Others: 0,07 kg</b>	
	<b>31,46%</b>		<b>14,13%</b>		<b>54,41%</b>

### Substances management

Socomec is leading a program to limit the use of hazardous substances in the design of new products and to monitor the presence of substances of concern in its supplies to anticipate future use restrictions.



Directive 2011/65/EU : Product references covered by this PEP meet the requirements of the RoHS Directive on the restriction of substances such as lead, mercury, cadmium, hexavalent chromium, polybrominated biphenyl (PBB), polybrominated diphenyl ethers (PBDEs) and phthalates (DIBP, DEHP, BBP, DBP).



REACH 1907/2006 regulation: To the best of our knowledge, based on the supplier declarations, at the publication date of this document, the product do not contain any SVHC in a concentration above 0,1% per weight.

## ● Manufacturing

The products covered by this PEP are manufactured on the production site of China a site where impacts on the environment are reduced by optimizing its energy consumption and by practicing a rigorous waste management. Moreover, Socomec is committed to the progressive ISO 14001 certification of its manufacturing sites.

## ● Distribution

As part of its distribution policy aiming to respect the environment, Socomec is in favor of groupage transports and ISO 14001 certified logistic partners.

No reconditioning is planned for the product. This phase is consequently neglected.  
The sizing of the packaging has been optimized to ensure the best possible protection of the product at the lowest possible volume in order to reduce the impact of the transport stage on the environment.

## ● Installation

The installation phase consists in connecting the product to the existing electrical installation.  
The installation does not generate any significant impacts on the environment, except impacts from packaging waste.

## ● Use phase

### Consumption scenario

Use phase scenario: European energy mix

Use phase scenario	Active 100% of the time	
Mode	Power of the reference product [W]	Time distribution [%]
Active	0,373	100%

Product power consumption during its total lifespan (10 years): 32,67 kWh

### Care and maintenance

The product does not require any maintenance under normal conditions of use.

### Consumables

The product does not require consumables.

## ● End of life

### End of life treatment

The following parts require specific care and selective treatment in accordance with Annex VII of the WEEE Directive 2012/19/EU - Waste of electrical and electronic equipment : *Printed circuit board*.

Maintenance and disassembly should always be conducted by qualified personnel.

### Recyclability potential of the product according to IEC TR 62635

The recovery recyclability of the product is 31,16%.  
This covers material and energy recovery potentials.

## ● Environmental impacts

### Calculation methodology: life cycle assessment (LCA)



The calculation of the impacts on the environment was made using a life cycle assessment methodology in accordance with the ISO 14040 requirements and with PEP eco passport product category rules.

For more details follow the link:

[www.pep-ecopassport.org](http://www.pep-ecopassport.org)

This study was carried out with the following version of the software EIME and of the database:

EIME version: 6.2.3

Database version: CODDE-2024-04 - updated on 2024-06-04

For biogenic carbon storage the following methodology was used : 0/0

The whole life cycle has been taken into account:

Step	Geographical representativeness	Scenario
<b>Manufacturing (M) (A1-A3)</b>	Production of electronic components : Asia Production of other components and packaging : China Assembly : China	From the raw material extraction to the last Socomec logistic platform, including packaging Waste generated during manufacturing phase are taken into account.
<b>Distribution (D) (A4)</b>	Distribution scenario : Europe	From the last Socomec logistic platform to the final customer.
<b>Installation (I) (A5)</b>	Transport and treatment of packaging wastes : Local	Local road transport of 1000 km of generated wastes to the treatment site, end of life treatment.
<b>Use phase (U) (B1-B7)</b>	Energy mix : Europe	Power consumption required during 20 years and maintenance according to consumption scenario above mentionned.
<b>End of life (EOL) (C1-C4)</b>	Transport and treatment : Local	Road transport of 1000 km from the final customer to the treatment sites. End of life treatment.

## Environmental impacts of the COUNTIS P04, per FU


The following impacts have been calculated to best represent geographically, temporally and technologically each step of the life cycle.

Indicators	Unit	Total impact	M (A1-A3)	D (A4)	I (A5)	U (B1-B7)	EOL (C1-C4)
Climate change	kg CO2 eq.	2,12E+01	9,47E+00	3,77E-02	1,40E-01	1,15E+01	9,44E-03
Climate change-Biogenic	kg CO2 eq.	7,64E-02	0*	0*	7,46E-02	2,12E-02	0*
Climate change-Fossil	kg CO2 eq.	2,11E+01	9,49E+00	3,77E-02	6,58E-02	1,15E+01	9,44E-03
Climate change-Land use and land use change	kg CO2 eq.	6,33E-05	6,33E-05	0*	0*	0*	0*
Ozone depletion	kg CFC-11 eq.	8,90E-07	8,34E-07	0*	1,57E-10	5,58E-08	1,61E-10
Acidification	mol H+ eq.	1,18E-01	5,80E-02	1,31E-03	2,16E-05	5,90E-02	4,68E-05
Eutrophication, freshwater	kg P eq.	5,35E-05	2,06E-05	1,30E-08	2,71E-07	3,03E-05	2,24E-06
Eutrophication, marine	kg N eq.	1,42E-02	6,61E-03	3,09E-04	6,55E-05	7,19E-03	1,73E-05
Eutrophication, terrestrial	mol N eq.	1,99E-01	8,01E-02	3,38E-03	8,35E-05	1,15E-01	1,86E-04
Photochemical ozone formation - human health	kg NMVOC eq.	4,59E-02	2,24E-02	8,71E-04	4,77E-05	2,26E-02	4,90E-05
Resource use, minerals and metals	kg SB eq.	7,36E-04	7,32E-04	0*	0*	4,07E-06	0*
Resource use, fossils	MJ	4,53E+02	1,61E+02	4,77E-01	4,54E-02	2,91E+02	1,36E-01
Water use	m3 eq.	2,62E+00	1,74E+00	0*	0*	8,82E-01	3,13E-04
Particulate matter	Disease occurrence	8,50E-07	3,68E-07	6,90E-09	1,51E-10	4,75E-07	3,41E-10
Ionising radiation, human health	kBq U235 eq.	2,69E+01	1,04E+01	0*	0*	1,66E+01	0*
Ecotoxicity, freshwater	CTUe	5,45E+01	3,21E+01	2,25E-02	5,41E-01	2,18E+01	7,19E-02
Human toxicity, cancer	CTUh	1,07E-08	9,22E-09	0*	7,13E-12	1,45E-09	2,69E-12
Human toxicity, non-cancer	CTUh	1,34E-07	9,95E-08	0*	1,46E-10	3,46E-08	1,48E-11
Land use	No dimension	5,87E-01	2,69E-01	0*	0*	3,19E-01	0*
Renewable primary energy used as energy	MJ	1,00E+02	2,31E+01	0*	0*	7,69E+01	0*
Renewable primary energy used as raw material	MJ	8,05E-01	8,05E-01	0*	0*	0*	0*
Total renewable primary energy	MJ	1,01E+02	2,39E+01	0*	0*	7,69E+01	0*
Non renewable primary energy used as energy	MJ	4,51E+02	1,59E+02	4,77E-01	4,54E-02	2,91E+02	1,36E-01
Non renewable primary energy used as raw material	MJ	2,01E+00	2,01E+00	0*	0*	0*	0*
Total non renewable primary energy	MJ	4,53E+02	1,61E+02	4,77E-01	4,54E-02	2,91E+02	1,36E-01
Total primary energy	MJ	5,54E+02	1,85E+02	4,77E-01	0*	3,68E+02	1,38E-01
Use of secondary material	kg	9,19E-04	9,19E-04	0*	0*	0*	0*
Use of renewable secondary fuels	MJ	0,00E+00	0*	0*	0*	0*	0*
Use of non renewable secondary fuels	MJ	0,00E+00	0*	0*	0*	0*	0*
Net use of fresh water	m3	6,12E-02	4,05E-02	0*	0*	2,07E-02	7,29E-06
Hazardous waste disposed	kg	1,05E+01	1,00E+01	0*	0*	5,05E-01	0*
Non hazardous waste disposed	kg	5,25E+00	3,17E+00	1,15E-03	4,20E-02	1,94E+00	9,19E-02
Radioactive waste disposed	kg	2,42E-03	1,97E-03	7,99E-07	4,00E-07	4,46E-04	2,63E-06
Components for reuse	kg	0,00E+00	0*	0*	0*	0*	0*
Materials for recycling	kg	5,76E-05	5,76E-05	0*	0*	0*	0*
Materials for energy recovery	kg	0,00E+00	0*	0*	0*	0*	0*
Exported Energy	MJ	0,00E+00	0*	0*	0*	0*	0*
Biogenic carbon content - Product	kg of C	0,00E+00	0*	0*	0*	0*	0*
Biogenic carbon content - Packaging	kg of C	1,40E-02	1,40E-02	0*	0*	0*	0*

NB : 0\* means that this impact either represents less than 0.01% of the total life cycle of the reference flow, or has no impact (in the case where the total impact is zero).

# PRODUCT ENVIRONMENTAL PROFILE

For the use stage (U), the product does not require maintenance therefore the impacts values are representatives of the B6 phase from the use stage : "Energy requirements during the use stage"

Registration number : SOCO-00113-V01.01-EN	Drafting Rules : "PEP-PCR-ed4-EN 2021 09 06"
Verifier accreditation number : VH46	Information and reference documents : <a href="http://www.pep-ecopassport.org">www.pep-ecopassport.org</a>
Date of issue: 11-2024	Validity period : 5 years
Independant verification of the declaration and data in compliance with ISO 14025 : 2006	
Internal : <input checked="" type="checkbox"/> External : <input type="checkbox"/>	
The PCR review was conducted by a panel of experts chaired by Julie Orgelet (DDemain)	
PEPs are compliant with XP C08-100-1 : 2016 or EN 50693:2019	
The components of the present PEP may not be compared with components from any other program.	
Document complies with ISO 14025:2006 "Environmental labels and declarations. Type III environmental declarations"	

*This document is intended to be only informative and non-contractual and does not create any right or obligation or commitment for Socomec towards its associates, customers or any other person or entity. All the values indicated in this document may change depending on many factors (use conditions, applications, installations, environment...). The life time mentioned in this document is only indicative and is not intended to be the minimal, maximal or average life time of the product.*

## Other references covered and extrapolation factors

For the products covered by the PEP other than the reference product, the environmental impacts of each phase of the lifecycle may be calculated with extrapolation factors following the proportionality rules that you can find below.

Extrapolation factors are determined as follows and can be provided upon request:

- For the Manufacturing and Distribution phases they are proportional to the mass of the product with its packaging;
- For the Installation phase they are proportional to the mass of the packaging;
- For the Use phase they are proportional to the power losses of the product;
- For the End of Life phase they are proportional to the mass of the product without its packaging.

Model	Part Number
COUNTIS P04	48505004
COUNTIS P06	48505006